



DATA SHEET

Hall Effect Current Sensor

PN: CHK_EKAD24S5

IPN=50-600A

Feature

- Open- loop current transducer using the hall effect
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Output signal can be directly acquisition-ed by the PLC or DSP terminal control system.
- Supply voltage: DC +12.0~+24.0V

Advantages

- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference
- Can be customized

Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



Electrical data: (Ta=25°C, Vc=+24.0VDC)

Ref Parmeter	CHK50EK AD24S5	CHK100E KAD24S5	CHK200E KAD24S5	CHK300E KAD24S5	CHK400E KAD24S5	CHK600E KAD24S5
Rated input Ipn(A)	50	100	200	300	400	600
Measuring range Ip(A)	0 ~ +100	0 ~ +200	0 ~ +400	0 ~ +600	0 ~ +800	0 ~ +1200
Output voltage DC Vo(V)	±5.0*(IP/IPN)					
Load resistance RL(KΩ)	>10					
Supply voltage Vc(V)	(+12.0~+24.0) ±5%					
Accuracy XG(%)	@IPN,T=25°C		< ±1.0			
Offset voltage VOE(mV)	@IP=0,T=25°C		<+40			
Temperature variation of VOE VOT(mV/°C)	@IP=0,-40 ~ +85°C		< ±1.0			
Hysteresis offset voltage VOH(mV)	@IP=0,after 1*IPN		<+20			
Linearity error εr(%FS)	< 1.0					
Response time tra(ms)	@90% of IPN		<20			
Power consumption IC(mA)	15					



Cheemi Technology Co., Ltd

Bandwidth Bw(KHZ)	@-3dB,IPN	DC-2.0
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	2.5

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55 ~ +125
Mass M(g)	70
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

CHK-EKAD24S5M	CHK-EKAD24S5S	Connection
		<p>General tolerance</p> <p>General tolerance: <math>\pm 0.5\text{mm}</math></p> <p>Primary through-hole : $D21.0 \pm 0.3$</p> <p>Connection of Secondary :</p> <p>CHK-EKAD5S2M: 2510-04A (Instead of Molex 5045-04A)</p> <p>CHK-EKAD5S2S: 15EDGK3.81-04P</p>

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be $< 100^{\circ}\text{C}</math>.$

WARNING : Incorrect wiring may cause damage to the sensor.



Cheemi Technology Co., Ltd
 Tel: 025-85996365 E-mail: info@cheemi-tech.com www.cheemi-tech.com
 Add: N22, Xianlongwan, Xianyin South Road, Qixia District, Nanjing - China.