



DATA SHEET

Hall Effect Current Sensor

PN: CHK_BR15D4

IPN=50-600A

Feature

- Open- loop
- Capable measurement of currents: DC, AC, pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC $\pm 12\sim 15V$

Advantages

- Excellent accuracy
- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference
- Very good linearity
- Can be customized

Applications

- Inverter applications
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Frequency drive control home appliances



RoHS



Electrical data: ($T_a=25^\circ C$, $V_c=\pm 15.0VDC$, $R_L=10K\Omega$)

Parameter	Ref	CHK50 BR15D4	CHK100 BR15D4	CHK200 BR15D4	CHK300 BR15D4	CHK400 BR15D4	CHK600 BR15D4
Rated input $I_{pn}(A)$		50	100	200	300	400	600
Measuring range $I_p(A)$		0 \sim ± 150	0 \sim ± 300	0 \sim ± 600	0 \sim ± 900	0 \sim ± 900	0 \sim ± 900
Output voltage $V_o(V)$		$\pm 4.0 * (I_p / I_{PN})$					
Load resistance $R_L(K\Omega)$		> 10					
Supply voltage $V_C(V)$		$(\pm 12 \sim \pm 15) \pm 5\%$					
Accuracy $X_G(\%)$		@IPN, $T=25^\circ C$		$< \pm 1.0$			
Offset voltage $VOE(mV)$		@IP=0, $T=25^\circ C$		$< \pm 25$			
Temperature variation of VOE $VOT(mV/^\circ C)$		@IP=0, $-40 \sim +85^\circ C$		$< \pm 1.0$			
Hysteresis offset voltage $VOH(mV)$		@IP=0, after 1*IPN		$< \pm 25$			
Linearity error $\epsilon_r(\%FS)$		< 1.0					
Di/dt accurately followed $(A/\mu s)$		> 100					
Response time $t_{ra}(\mu s)$		@90% of IPN		< 3.0			
Power consumption $I_C(mA)$		15					
Bandwidth $B_w(KHZ)$		@-3dB, IPN		DC-20			



Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	2.5
---------------------------	-------------------	-----

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	70
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	<p style="text-align: center;">Connection</p>
	<p style="text-align: center;">General tolerance</p> <p>General tolerance: <math>\pm 0.5\text{mm}</math> Primary through-hole : <math>10.5 \times 20.5 \pm 0.3</math> Connection of secondary : 4 core cable length L=650mm;</p>

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole if fully filled with.
- The primary conductor should be <math>< 100^{\circ}\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.

