



DATA SHEET

Hall Effect Current Sensor

PN: CHB_SYA15D20

IPN=05~50A

Feature


- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC, pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC $\pm 12\sim 15V$
- PCB installation

Advantages

- High accuracy
- Easy installation
- Low temperature drift
- Optimized response time
- High immunity to external interference
- Very good linearity
- Can be customized

Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS

Electrical data: (Ta=25°C, Vc= ±15VDC)

Parmeter	CHB05SY A15D20	CHB10SY A15D20	CHB15SY A15D20	CHB20SY A15D20	CHB30SY A15D20	CHB50SY A15D20
Rated input Ipn(A)	05	10	15	20	30	50
Measuring range Ip(A)	0 ~ ±10	0 ~ ±20	0 ~ ±30	0 ~ ±40	0 ~ ±60	0 ~ ±100
Size of Input pin *d (MM)	Ø0.8	Ø0.8	Ø1.0	Ø1.4	Ø1.6	2×□1.6×1.5
Turns ratio Np/NS (T)	4:1000	3:1500	2:1500	1:1000	1:1500	1:2500
Inside resistance RM (Ω)	50~400±0.1%					
Output current rms IS(mA)	±20.0*(IP/IPN)					
Supply voltage VC(V)	(±12 ~ ±15) ±5%					
Accuracy XG(%)	@IPN, T=25°C		< ±0.5			
Offset current IOE(mA)	@IP=0, T=25°C		< ±0.2			
Temperature variation of IOE IOT(mA/°C)	@IP=0, -40 ~ +85°C		< ±0.005			
Linearity error er(%FS)	< 0.1					
Di/dt accurately followed (A/μs)	> 50					
Response time tra(μs)	@90% of IPN		< 1.0			



Cheemi Technology Co., Ltd

Tel: 025-85996365

E-mail: info@cheemi-tech.com

www.cheemi-tech.com

Add: N22, Xianlongwan, Xianyin South Road, Qixia District, Nanjing - China.

Cheemi Technology Co., Ltd

Power consumption IC(mA)		15+Is
Bandwidth BW(KHZ)	@-3dB,IPN	DC-100
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	5.0

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	12
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

I _{pn} <50A	I _{pn} =50A	Connection
		General tolerance
		General tolerance: $\leq \pm 0.5\text{mm}$ Secondary Pin size : $0.25 \times 0.5 \pm 0.1\text{mm}$

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^\circ\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.



Cheemi Technology Co., Ltd
 Tel: 025-85996365 E-mail: info@cheemi-tech.com www.cheemi-tech.com
 Add: N22, Xianlongwan, Xianyin South Road, Qixia District, Nanjing - China.